

## Version Update (v3.4.3) For Eye-Sight IPC

Dear Partner,

We are happy to announce the release of version 3.4.3 for our Eye-Sight IPC Series. The update covers the following models:

### Eye-Sight 3MP

- 1) [DAI-330IP536](#)
- 2) [DAI-330IP5VF](#)
- 3) [I3-330IP536](#)
- 4) [I4-330IPVF](#)

### Eye-Sight 4MP

- 1) [BX-342IP5](#)
- 2) [DAI-340IP536](#)
- 3) [DAI-340IP5VF](#)
- 4) [I3-340IP536](#)
- 5) [I4-340IP5VF](#)

### Main improvements:

- 1) True WDR Support
- 2) HLC Support
- 3) BLC Support
- 4) SD-Card video recording (Recording Sub-Stream, for supported models only)
- 5) SNMP Support
- 6) HFR (High Frame Rate) Support (Enabling HFR will disable the True WDR)

### Update Process:

This update requires 3 update steps in order to complete successfully.

- 1) Download the correct firmware (From Provision-ISR Website or by clicking on the camera name above)
- 2) Unpack the RAR file, run "Upgrade Tool.exe" and complete the following steps:
  - a. Choose all the cameras you wish to update (must be from the same model)
  - b. Choose "Update Uboot" from the drop-down menu.
  - c. Click on "browse" and choose the Uboot file: U-Boot-xxxxxxx-Eye-Sight-201
  - d. Confirm the username/password (Default is admin/123456)
  - e. Click on "Upgrade" and wait. Once the process is finished the camera will reboot.
  - f. Select the cameras again.
  - g. Choose "Update Kernel" from the drop-down menu.
  - h. Click on "browse" and choose the Kernel file: Kernel-xxxxxxx-Eye-Sight-201
  - i. Click on Upgrade and wait. Once the process is finished the camera will reboot.

Upgrade Tool 4.0.1.2

| Camera...                           | IP Address | MAC address   | Produc...  | Softwa...  | Softwa... | Kernel ... | Result |
|-------------------------------------|------------|---------------|------------|------------|-----------|------------|--------|
| <input type="checkbox"/> DI-390I... | 10.0.0.45  | 00:18:AE:8... | Provisi... | 4.0.2      | 20160...  | 20160...   |        |
| <input type="checkbox"/> DAI-39...  | 10.0.0.46  | 00:18:AE:4... | Provisi... | 3.4.1      | 20140...  | 20140...   |        |
| <input type="checkbox"/> DI-390I... | 10.0.0.68  | 00:18:AE:4... | Provisi... | 3.4.1      | 20140...  | 20140...   |        |
| <input type="checkbox"/> 9442E2...  | 10.0.0.29  | 00:18:AE:4... | Provisi... | 3.4.1      | 20140...  | 20140...   |        |
| <input type="checkbox"/> IP cam...  | 10.0.0.98  | 00:18:AE:4... | Provisi... | 3.4.2      | 20150...  | 20140...   |        |
| <input type="checkbox"/> DAI-31...  | 10.0.0.32  | 00:18:AE:4... | Provisi... | 3.4.1      | 20140...  | 20140...   |        |
| <input type="checkbox"/> name       | 10.0.0.27  | 00:18:AE:4... | Provisi... | 3.4.1      | 20140...  | 20140...   |        |
| <input type="checkbox"/> DAI-31...  | 10.0.0.30  | 00:18:AE:4... | Provisi... | 3.4.1      | 20140...  | 20140...   |        |
| <input type="checkbox"/> IP Cam...  | 10.0.0.31  | 00:18:AE:4... | Provisi... | 3.4.1      | 20140...  | 20140...   |        |
| <input type="checkbox"/> DEVICE...  | 10.0.0.48  | 00:18:AE:4... | 9443E1     | 3.4.2.b... | 20150...  | 20140...   |        |
| <input type="checkbox"/> name       | 10.0.0.80  | 00:18:AE:5... | Provisi... | 3.4.3      | 20160...  | 20160...   |        |
| <input type="checkbox"/> I4-340I... | 10.0.0.201 | 00:18:AE:5... | Provisi... | 3.4.3      | 20160...  | 20160...   |        |
| <input type="checkbox"/> name       | 10.0.0.26  | 00:18:AE:5... | 9632E2     | 4.0.1.b... | 20160...  | 20150...   |        |
| <input type="checkbox"/> name       | 10.0.0.28  | 00:18:AE:4... | Provisi... | 3.4.1      | 20140...  | 20140...   |        |

Select All Clear All Choose all from same type

Batch Upgrade

Normal

Update Software

Update Software

Update Kernel

Update Uboot

Upgrade

Choose the cameras you wish to update (Must be from the same model)

Confirm Username/Password

Update all (Uboot, Kernel, Software)

Please do not hesitate to contact us with any question/concern you might have.

Best Regards,  
Provision-ISR Technical Department.