


Ossia FW update from v1.0.3 or higher to v1.3.3

- 1) If your Ossia recorder running with v1.0.2 or lower, please do not use this version & contact Provision-ISR tech support team for assistant.
- 2) This update will reset all setting to factory default. From this version and onwards – update will be applied via our servers directly from the Ossia OS & will keep the whole system setting.
- 3) This update is a “Flash burning process”, please extract the files from the “zip” pack And copy to the root directory of USB pen FAT32 – MBR (Master boot record).

Insert the USB pen with files to the recorder & restart, this update will take about ~7 minutes.

Recorder will reboot several times during the update – do not interfere till the recorder will finish startup & will display the live view display with wizard.

- 4) **If you are using the USB pen with files to update several recorders (from the same model), You will have to move the USB pen to PC & delete the file named: “skipupgrade2” as shown below:**

 skipupgrade2

This file is created during the update process to avoid recorder from upgrading in a loop, and should be deleted in the end of every update process – for allowing the USB pen able to update the next recorder.

- 5) In case of the device is not finishing update & normal startup process within 15 minutes, please disconnect & reconnect the power.

Best Regards,
Provision-ISR Technical support team.